

# RHEL

Red Hat Enterprise Linux; Alama Linux

- [Print Server](#)
  - [Installing CUPS server](#)
  - [CUPS ClientNew Page](#)

# Print Server

# Installing CUPS server

To install the server the cupsd package and dependencies need to be downloaded.

```
dnf install cups -y
```

After installation only a couple of items need to be changed under

```
/etc/cups/cupsd.conf
```

Find Listen 127.0.0.1:631 and replace with

```
Listen *:631
```

Confirm the following is enabled

```
Browsing On
BrowseLocalProtocols dnssd
```

Edit these two sections as follows

```
# Restrict access to the server...
<Location />
  Order allow,deny
  Allow @LOCAL
</Location>

# Restrict access to the admin pages...
<Location /admin>
  AuthType Default
  Require valid-user
  Order allow,deny
  Allow @LOCAL
</Location>
```

This line can be added near the top if a 400 bad request is happening due to DNS problems or the gold image that is being used.

ServerAlias \*

Save. Now add the firewall rules

```
firewall-cmd --add-port=631/tcp --permanent  
firewall-cmd --reload
```

Restart cups

```
systemctl restart cups
```

# CUPS ClientNew Page

Under the cups client we need to prevent the discovery of networked printers in order to only use the new print server. Bonjour may also need to be disabled on the printer itself. It doesn't always stop the printer from adding. However, this is the first measure. Edit the file.

```
/etc/cups/cups-browsed.conf
```

Find

```
BrowseRemoteProtocols dnssd cups
```

Replace with

```
BrowseRemoteProtocols none  
BrowseProtocols none
```

Edit the file.

```
/etc/cups/cupsd.conf
```

Find

```
Browsing On  
BrowseLocalProtocols dnssd
```

Replace with

```
Browsing No  
BrowseLocalProtocols none
```

Restart CUPS service.

```
systemctl restart cups
```